

DESCRIPTION

The EV8846-Q-00A is used for demonstrating the performance of MPS's MP8846. MP8846 is a highly integrated and high frequency synchronous step-down switcher with I²C control interface. It is optimized to support up to 6A load current over an input supply range from 4.5V to 8V with excellent load and line regulation.

Current-Mode operation provides fast transient response and eases loop stabilization. The reference voltage level can be controlled, on-the fly through a 3.4Mbps I²C serial interface. The voltage range can be adjusted from 0.6V to 1.87V in 10mV steps. The voltage slew rate, switching frequency and power savings mode are also selectable through the I²C interface. Fully protection features includes over current protection, over voltage protection and over temperature protection.

MP8846 is available in QFN15 (3mmx3mm) package.

ELECTRICAL SPECIFICATION

Parameter	Symbol	Value	Units
Input Voltage	V _{IN}	4.5– 8	V
Output Voltage	V _{OUT}	1.2	V
Output Current	I _{OUT}	6	A

FEATURES

- Wide 4.5V-to-8V Operation Input Range
- 45mΩ/18mΩ Low R_{DS(ON)} Internal Power MOSFETs
- 1% V_{OUT} Accuracy
- I²C Programmable Reference Range from 0.6V to 1.87V in 10mV Steps with Slew Rate Control
- I²C Selectable Switching Frequency. Default 600kHz Switching Frequency.
- Programmable Output Voltage
- Power Saving Mode, OTP and OCP Via I²C
- Power Good Indication
- 1 bit I²C Address Set pin
- OCP Protection and Hiccup
- External Soft Start
- Available in QFN3mmx3mm Package

APPLICATIONS

- Flat-Panel Television and Monitors
- Digital Set-Top Boxes
- Distributed Power Systems


All MPS parts are lead-free, halogen free, and adhere to the RoHS directive. For MPS green status, please visit MPS website under Quality Assurance.

"MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.


EV8846-Q-00A EVALUATION BOARD



Board Number	MPS IC Number
EV8846-Q-00A	MP8846GQ



EVALUATION BOARD SCHEMATIC



EV8846-Q-00A BILL OF MATERIALS


Qty	RefDes	Value	Description	Package	Manufacturer	Manufacturer P/N
1	C1	0.22µF	Ceramic Cap., 16V, X7R	0603	muRata	GRM188R71C224KA01D
2	C2,C8	22µF	Ceramic Cap., 25V, X5R	1206	muRata	GRM31CR61E226KE15L
2	C3,C4	0.1µF	Ceramic Cap., 25V, X7R	0603	muRata	GRM188R71E104KA01D
2	C5,C6	22µF	Ceramic Cap., 10V, X5R	1206	muRata	GRM31CR61A226ME19L
1	C7	22nF	Ceramic Cap., 50V, X7R	0603	muRata	GRM188R71H223KA01D
1	C10	10pF	Ceramic Cap., 50V, C0G	0603	muRata	GRM1885C1H100JA01D
1	C11	22pF	Ceramic Cap., 50V, C0G	0603	muRata	GRM1885C1H220JA01D
0	C9, C12	NS				
2	R1, R2	34k	Thick Film Res., 1%	0603	Yageo	RC0603FR-0734KL
1	R3	33k	Thick Film Res., 1%	0603	Yageo	RC0603FR-0733KL
3	R4,R7,R9	100k	Thick Film Res., 1%	0603	Yageo	RC0603FR-07100KL
1	R5,R8	10Ω	Thick Film Res., 1%	0603	Yageo	RC0603FR-0710RL
0	R6	NS				
1	L1	1µH	Inductor,DCR=4.6mΩ, Is=19A	6.9×6.9×3.8mm	Wurth	744311100
1	U1	MP8846GQ	Synchronous Step-Down Convert	QFN3mmx3mm	MPS	MP8846GQ

EVB TEST RESULTS


Performance waveforms are tested on the evaluation board.

$V_{IN} = 5V$, $V_{OUT} = 1.2V$, $L = 1\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Efficiency vs. Output Current




Case Temperature Rise vs. Load Current



Load Regulation



Line Regulation




EVB TEST RESULTS *(continued)*

Performance waveforms are tested on the evaluation board.

$V_{IN} = 5V$, $V_{OUT} = 1.2V$, $L = 1\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Short Entry

$I_{OUT} = 0A$




Short Recovery

$I_{OUT} = 0A$




Start-Up through Enable

$I_{OUT} = 0A$




Start-Up through Enable

$I_{OUT} = 6A$




Shutdown through Enable

$I_{OUT} = 0A$




Shutdown through Enable

$I_{OUT} = 6A$




Start-Up through Input Voltage

$I_{OUT} = 0A$




Start-Up through Input Voltage

$I_{OUT} = 6A$



Shutdown through Input Voltage

$I_{OUT} = 0A$




EVB TEST RESULTS *(continued)*

Performance waveforms are tested on the evaluation board.

$V_{IN} = 5V$, $V_{OUT} = 1.2V$, $L = 1\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Shutdown through Input Voltage

$I_{OUT} = 6A$




Input/Output Ripple

$I_{OUT} = 6A$




Input/Output Ripple

$I_{OUT} = 0A$




Load Transient Response

$I_{OUT} = 3A$ to $6A$




I²C Control Slew Rate

Slew Rate=16mV/µs, $I_{OUT} = 0A$, from 0.9V to 1.2V




I²C Control Slew Rate

Slew Rate=16mV/µs, $I_{OUT} = 0A$, from 1.2V to 0.9V




I²C Control Slew Rate

Slew Rate=16mV/µs, $I_{OUT} = 3A$, from 0.9V to 1.2V



I²C Control Slew Rate

Slew Rate=16mV/µs, $I_{OUT} = 3A$, from 1.2V to 0.9V



PRINTED CIRCUIT BOARD LAYER




Figure 1: Top Silk Layer




Figure 2: Top Layer




Figure 3: Inner 1 Layer




Figure 4: Inner 2 Layer




Figure 5: Bottom Layer

QUICK START GUIDE

1. Connect the positive and negative terminals of the load to the VOUT and GND pins, respectively.
2. Preset the power supply output between 4.5V and 8V, and then turn off the power supply.
3. Connect the positive and negative terminals of the power supply output to the VIN and GND pins, respectively.
4. Turn the power supply on. The board will automatically start up.
5. To use the Enable function, apply a digital input to the EN pin. Drive EN higher than 1.4V to turn on the regulator, or less than 1.25V to turn it off.
6. To program I²C function, connect SCL, SDA and GND to I²C start kit board. Connect I²C start kit board to computer and run MP8846 GUI software to program MP8846 I²C register.

NOTICE: The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.