



The Future of Analog IC Technology®

EV103-N-00A Offline Inductor-Less Controller EV Board

DESCRIPTION

The MP103 is a good efficiency off-line linear regulator that directly steps down the AC line voltage to a regulated DC voltage. It provides a simple solution to provide a bias voltage to any ICs in the off-line application. Off-line linear regulator is designed to replace the conventional switching converter; it features no inductor required, low EMI noise and low BOM cost.

MP103 features as a controller that supports to drive low cost bipolar junction transistor. MP103 integrates an adaptive active VB-VOUT charging window method. The MP103 only works when it is necessary and only when the loss generated on the device is minimal. Such operation can achieve good efficiency and can help the system meet the new standby power specification.

MP103 offers rich protections, such as Thermal Shutdown (TSD), Over Temperature Protection (OTP), VB Over Voltage Protection (OVP), VB Short to GND Protection, Over Load Protection (OLP), Short Circuit Protection (SCP), MP103 is available in the SOIC8E package.

ELECTRICAL SPECIFICATION

| Parameter | Symbol | Value | Units |
|----------------|-----------|--------|-------|
| Supply Voltage | V_{IN} | 85~265 | VAC |
| Output Voltage | V_{OUT} | 5 | V |
| Output Current | I_{OUT} | 60 | mA |

FEATURES


- Universal AC Input (85Vac-305Vac)
- Inductor-Less
- Less than 100mW Standby Power
- Excellent EMI
- Low BOM Cost
- Smart Control to Maximum Efficiency
- Adjustable Output Voltage from 1.5V to 15V
- Good Line and Load Regulation
- Support to Drive BJT
- Short Circuit Protection
- External Programmable Over Temperature Protection (OTP)

APPLICATIONS

- Wall Switches and Dimmers
- Z-Wave Device and ZigBee Device for Home Automation
- Standby Power for General Off-line Applications

All MPS parts are lead-free and adhere to the RoHS directive. For MPS green status, please visit MPS website under Quality Assurance. "MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.


EV103-N-00A EVALUATION BOARD



(L x W x H) 22mm x 24mm x 24mm

| Board Number | MPS IC Number |
|--------------|---------------|
| EV103-N-00A | MP103GN |

EVALUATION BOARD SCHEMATIC




VOUT can be adjusted by choosing the value of R4 and R5, the relationship of them is:

$$V_{OUT} = 1.235V * (1 + R5/R4)$$

For example, to get 12V output voltage, we can choose, R4=10.2k, R5=90.9k.

The maximum output power (P_{OUT}) of MP103 Vs input voltage (V_{IN}) is depicted by following chart for 12V, 5V and 3.3V output applications respectively.

The test condition is: in open frame, ambient temperature is 25 °C, the temperature rise of MP103 is less than 60 °C on the test board.



EV103-N-00A BILL OF MATERIAL


| Qty | Ref | Value | Description | Package | Manufacture | Manufacturer_PN |
|-----|-----------|----------------|---------------------------------|---------|----------------------|--------------------|
| 1 | BD1 | MB6S | Diode;600V;0.5A; | SOIC-4 | TaiWan Semiconductor | MB6S |
| 1 | C1 | 470 μ F | Electrolytic Capacitor; 25V; | DIP | Jianghai | CD287-25V470 |
| 1 | C2 | 4.7 μ F | Ceramic Capacitor; 16V; | 0805 | Murata | GRM21BR61C475KA88L |
| 1 | C3 | 1nF | Ceramic Capacitor; 16V;X7R; | 0603 | Murata | GRM188R71C102KA01 |
| 1 | C4 | 4.7 μ F | Electrolytic Capacitor; 50V; | DIP | Jianghai | CD287-50V4.7 |
| 1 | C5 | 100nF | Ceramic Capacitor; 16V;X7R; | 0603 | LION | 0603B104K160T |
| 1 | C6 | 20pF | Ceramic Capacitor; 50V;NPO; | 0603 | HHEC | C0603N200J050T |
| 1 | CX1 | 100nF | Film Capacitor; 275V;10% | DIP | Kaili | PX104K31C39L270D9R |
| 1 | Q1 | 3DD4802A | BJT,750V,1.5A; | TO-220F | Huawei | 3DD4802A |
| 1 | R1 | 10 Ω | Film Resistor;5%; | 1206 | Yageo | RC1206JR-0710R |
| 1 | R2 | 2k Ω | Film Resistor;5%; | 1206 | Royalohm | 1206F2001T5E |
| 2 | R3, R5 | 10.2k Ω | Film Resistor;1%; | 0603 | Yageo | RC0603FR-0710K2L |
| 1 | R4 | 30.9k Ω | Film Resistor;1%; | 0603 | Yageo | RC0603FR-0730K9L |
| 1 | RF | 10 Ω | Resistor;5%;1W | DIP | Bangdayuan | 10 Ohm/1W |
| 1 | RT1 | 10k Ω | NTC Resistor;5%; | DIP | Shiheng | MF52A103J3470F |
| 1 | RV | 275Vac | TVR10431KSY, 430V(1mA); | DIP | TKS | TVR10431KSY |
| 1 | U1 | MP103 | Offline Regulator | SOIC8E | MPS | MP103GN |

EVB TEST RESULTS


Performance waveforms are tested on the evaluation board.

$V_{OUT} = 5V$, $I_{OUT} = 60mA$, $T_A = 25^{\circ}C$, unless otherwise noted.


Efficiency vs. Load




No Load Power vs. Input Voltage




Input Power Startup
115Vac, 5V/60mA




Input Power Startup
230Vac, 5V/60mA




Steady State
115Vac, 5V/60mA




Steady State
230Vac, 5V/60mA



Input Power Shutdown
115Vac, 5V/60mA



Input Power Shutdown
230Vac, 5V/60mA




EVB TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board.


 $V_{OUT} = 5V$, $I_{OUT} = 60mA$, $T_A = 25^{\circ}C$, unless otherwise noted.

Output Ripple


115Vac, 5V/60mA


Output Ripple


230Vac, 5V/60mA


Load Transient


115Vac, 5V, 0 to 60mA


Load Transient


230Vac, 5V, 0 to 60mA


Over Load Protection Entry


115Vac


Over Load Protection Entry


230Vac


Over Load Protection Recovery


115Vac


Over Load Protection Recovery

230Vac


Short Circuit Protection Entry

115Vac




EVB TEST RESULTS *(continued)*


Performance waveforms are tested on the evaluation board.

$V_{OUT} = 5V$, $I_{OUT} = 60mA$, $T_A = 25^{\circ}C$, unless otherwise noted.


**Short Circuit
Protection Entry**
230Vac




**Short Circuit
Protection Recovery**
115Vac




**Short Circuit
Protection Recovery**
230Vac




**VB Short to GND
Protection Entry**
115Vac




**VB Short to GND
Protection Entry**
230Vac




**VB Short to GND
Protection Recovery**
115Vac




**VB Short to GND
Protection Recovery**
230Vac



RT Protection Entry
115Vac



RT Protection Entry
230Vac




EVB TEST RESULTS *(continued)*


Performance waveforms are tested on the evaluation board.

$V_{OUT} = 5V$, $I_{OUT} = 60mA$, $T_A = 25^{\circ}C$, unless otherwise noted.


RT Protection Recovery
115Vac




RT Protection Recovery
230Vac




Thermal Shutdown Protection Entry
115Vac




Thermal Shutdown Protection Entry
230Vac



Thermal Shutdown Protection Recovery
115Vac



Thermal Shutdown Protection Recovery
230Vac




EVB TEST RESULTS *(continued)*


Performance waveforms are tested on the evaluation board.

$V_{OUT} = 5V$, $I_{OUT} = 60mA$, $T_A = 25^{\circ}C$, unless otherwise noted.


EMI Performance
115Vac, L Line




EMI Performance
115Vac, N Line



EMI Performance
230Vac, L Line



EMI Performance
230Vac, N Line



PRINTED CIRCUIT BOARD LAYOUT




Figure 1 — Top Silk Layer




Figure 2 — Top Layer




Figure 3 — Bottom Silk




Figure 4 — Bottom Layer

QUICK START GUIDE

1. Preset Power Supply to $85V \leq V_{IN} \leq 265V$.
2. Turn Power Supply off.
3. Connect the Line and Neutral terminals of the power supply output to L and N ports.
4. Connect Load to VO and GND ports.
5. Turn Power Supply on after making connections.

NOTICE: The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.