

DESCRIPTION

The MPQ3426 is a current-mode step-up converter with a 6A, 90mΩ internal switch that provides a highly efficient regulator with a fast response. The MPQ3426 features a programmable frequency of up to 2MHz that allows for easy filtering and reduces noise. An external compensation pin gives the user flexibility in setting loop dynamics, and uses small, low-ESR, ceramic output capacitors. Soft-start results in a small inrush current and can be programmed with an external capacitor. The MPQ3426 operates from an input voltage as low as 3.2V and can generate up to a 35V output.

The MPQ3426's features include under-voltage lockout, current limiting, and thermal overload protection. The MPQ3426 is available in a low profile 14-pin 3mm×4mm QFN package with an exposed pad.

FEATURES

- 6A, 90mΩ, 45V Power MOSFET
- Uses Very Small Capacitors and Inductors
- Wide Input Range: 3.2V to 22V
- Output Voltage as High as 35V
- Programmable f_{sw} : 300kHz to 2MHz
- Programmable UVLO, Soft-Start, UVLO Hysteresis
- Micropower Shutdown <1μA
- Thermal Shutdown 160°C
- Available in 14-Pin 3mm×4mm QFN Package

APPLICATIONS

- Telecom—Power Supplies
- Audio—Microphone and Tuner Bias
- Automotive

All MPS parts are lead-free and adhere to the RoHS directive. For MPS green status, please visit MPS website under Quality Assurance. MPS[®] and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.

ELECTRICAL SPECIFICATIONS

Parameter	Symbol	Value	Units
Input Voltage	V_{IN}	6-9	V
Output Voltage	V_{OUT}	12	V
Output Current	I_{OUT}	2	A


EVQ3426-L-00A EVALUATION BOARD



(L x W x H) 2.5" x 2.5" x 0.4"
(6.35cm x 6.35cm x 1.0cm)

Board Number	IC Number
EVQ3426-L-00A	MPQ3426DL

Efficiency




QUICK START GUIDE

The output voltage of this board is set to 12V. The frequency is set to 600kHz. The board layout accommodates most commonly used inductors and output capacitors.

1. Preset the power supply to $6V \leq V_{IN} \leq 9V$.
2. Turn the power supply off.
3. Connect the power supply terminals to:
 - a. Positive (+): VIN
 - b. Negative (-): GND
4. Connect the load to:
 - a. Positive (+): VOUT
 - b. Negative (-): GND
5. Make sure the CN1 jumper is installed
6. Turn the power supply on after making the connections.
7. The MPQ3426 is enabled on the evaluation board once VIN is applied.
8. The output voltage VOUT can be changed by varying R2. Calculate the new value using the formula: $R2 = \left(\frac{V_{OUT}}{V_{FB}} - 1\right) \times R3$
Where VFB = 1.225V and R3=20k Ω
9. The frequency can be changed by adjusting R5. The formula is: $F_{SET} = 23 \times (R5^{-0.86})$
Where FSET is in MHz and R5 is in k Ω

EVALUATION BOARD SCHEMATIC




EVQ3426-L-00A BILL OF MATERIALS

Qty	Ref	Value	Description	Package	Manufacturer	Manufacturer P/N
1	C1	22 μ F	Ceramic Cap., 50V, 10%, X7R	1210	muRata	GRM32ER71H226ME15L
1	C2	0.1 μ F	Ceramic Cap., 25V, 10%, X7R	0603	muRata	GCJ188R71E104KA12D
2	C3,C4	22 μ F	Ceramic Cap., 25V, 10%, X5R	1210	muRata	GRM21BR61E226ME44L
1	C5	33nF	Ceramic Cap., 16V, 10%, X7R	0603	muRata	GRM188R71C333KA01D
	C6,C8	NS		0603		
1	C7	5.6nF	Ceramic Cap., 25V, 10%, X7R	0603	muRata	GRM188R71H562KA01D
1	C9	1 μ F	Ceramic Cap., 25V, 10%, X7R	0603	muRata	GCM188R71E105KA64D
1	CN1		2 Pin Header, 2.54mm	2.54mm	Sullins	PCC02SAAN
1	CN1	SHUNT	Short Jumper, 2.54mm	2.54mm	Sullins	STC02SYAN
1	D1	STPS5L60	Schottky Diode, 60V, 5A	SMB	ST Microelec	STPS5L60U
0	J1	NS				
1	L1	5.5 μ H	Inductor, I _{dc} 10A, R _{dc} 10.3m Ω	10.5x10.5mm	Würth	744325550
1	R1	100k	Film Res., 5%	0603	Yageo	RC0603JR-07100KL
1	R2	178k	Film Res., 1%	0603	Yageo	RC0603FR-07178L
2	R3, R6	20k	Film Res., 1%	0603	Yageo	RC0603FR-0720KL
1	R4	43.2k	Film Res., 5%	0603	Yageo	RC0603JR-0743K2L
1	R5	66.5k	Film Res., 5%	0603	Yageo	RC0603JR-0766K5L
1	R7	0 Ω	Film Res., 5%	0603	Yageo	RC0603JR-070RL
1	U1		Boost Converter	QFN14,3x4mm	MPS	MPQ3426 R12


EVB TEST RESULTS

Performance waveforms are tested on the evaluation board.


Efficiency




Line Regulation




Load Regulation




Case Temperature Rising vs. Load Current




V_{FB} Voltage vs. T_A




I_Q Current vs. T_A




Current Limit vs. T_A



V_{IN} UVLO Voltage vs. T_A



F_{SW} Frequency vs. T_A




EVB TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board.


Steady State

$V_{IN} = 6V, V_{OUT} = 12V/0A$




Steady State

$V_{IN} = 6V, V_{OUT} = 12V/2A$




V_{IN} Start Up

$V_{IN} = 6V, V_{OUT} = 12V/0A$




V_{IN} Start Up

$V_{IN} = 6V, V_{OUT} = 12V/2A$




V_{IN} Shutdown

$V_{IN} = 6V, V_{OUT} = 12V/0A$




V_{IN} Shutdown

$V_{IN} = 6V, V_{OUT} = 12V/2A$




EN Startup

$V_{IN} = 6V, V_{OUT} = 12V/0A$




EN Startup

$V_{IN} = 6V, V_{OUT} = 12V/2A$



EN Shutdown

$V_{IN} = 6V, V_{OUT} = 12V/0A$




EVB TEST RESULTS *(continued)*

Performance waveforms are tested on the evaluation board.


EN Shutdown

$V_{IN} = 6V, V_{OUT} = 12V/2A$




Load Transient

$V_{IN} = 6V, V_{OUT} = 12V,$
 $I_{OUT} = 0 \text{ to } 1A, I_{RAMP} = 10mA/\mu s$



Load Transient

$V_{IN} = 6V, V_{OUT} = 12V,$
 $I_{OUT} = 1 \text{ to } 2A, I_{RAMP} = 10mA/\mu s$



PRINTED CIRCUIT BOARD LAYOUT




Figure 1—Top Silk Layer




Figure 2—Top Layer




Figure 3—Bottom Layer

NOTICE: The information in this document is subject to change without notice. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.